
Resolution of Consumer Facing Switching and Billing Issues

Contents

Section A: General Obligations

1	Introduction.....	5
2	Consumer Principles and Outcomes.....	<u>Error! Bookmark not defined.</u> 5
3	Escalation of Delayed and Disputed Resolutions.....	7

Section B: Erroneous Switch

4	Description of the Problem.....	9
5	Resolution Outcomes	10
6	Resolution Process.....	12

Section C: Switch Meter Reading Problems

7	Description of the Problem.....	17
8	Resolution Outcomes	18
9	Resolution Process.....	19

Section D: Crossed Meters

10	Description of the Problem.....	26
11	Resolution Outcomes	26
12	Resolution Process.....	27

Section E: Duplicate RMPs

13	Description of the Problem.....	<u>3333</u>
14	Resolution Outcomes	<u>3333</u>
15	Resolution Process.....	<u>3333</u>

Section F: Misdirected Payments

16	Description of the Problem.....	<u>4144</u>
17	Resolution Outcomes	<u>4144</u>
18	Resolution Process.....	<u>4242</u>

Section G: Debt Assignment

19	Description of the Problem.....	<u>4545</u>
20	Resolution Outcomes	<u>4646</u>
21	Resolution Process.....	<u>4646</u>

Appendix 1: Advanced Meter Half-Hourly Data Sharing template



SCHEDULE 30

Resolution of Consumer-Facing Switching and Billing Problems

Version: 4.03-1Effective Date: Code Manager Licence Commencement Date~~07 November 2025~~

	Section A: General Obligations	Section B: <u>Erroneous Switches</u>	Section C: Switch Meter Read Problems	Section D: <u>Crossed Meters</u>	Section E: <u>Duplicate RMPs</u>	Section F: <u>Misdirected Payments</u>	Section G: Debt Assignment
<u>Domestic Suppliers</u>	<u>Mandatory</u>	<u>Mandatory</u>	<u>Mandatory</u> ¹	<u>Mandatory</u>	<u>Mandatory</u>	<u>Mandatory</u>	<u>Mandatory</u>
Gas <u>Non-Domestic Suppliers</u>	<u>Mandatory</u>	<u>Voluntary</u>	<u>Voluntary</u>	<u>Voluntary</u>	<u>Voluntary</u>	<u>Voluntary</u>	N/A
Electricity <u>Non-Domestic Suppliers</u>	<u>Mandatory</u>	<u>Mandatory</u> ¹	<u>Mandatory</u> ¹	<u>Mandatory</u>	<u>Mandatory</u>	<u>Mandatory</u>	N/A
<u>Gas Transporters</u>	<u>Mandatory</u>	N/A	N/A	<u>Mandatory</u>	<u>Mandatory</u>	N/A	N/A
<u>Distribution Network Operators</u>	<u>Mandatory</u>	N/A	N/A	<u>Mandatory</u>	<u>Mandatory</u>	N/A	N/A
<u>DCC</u>	<u>Mandatory</u>	N/A	N/A	N/A	N/A	N/A	N/A
<u>Meter Equipment Manager</u> s	N/A	N/A	N/A	<u>Mandatory</u>	<u>Mandatory</u>	N/A	N/A
<u>Non-Party REC Service Users</u>	N/A	N/A	N/A	N/A	N/A	N/A	N/A

1. This process is mandatory for all electricity Metering Points with the exception that it is Voluntary for HH Non-MHHS Metering Points and Unmetered Supply Non-MHHS Metering Points.

Modification ~~Change~~ History

Version Number	Implementation Date	Reason for <u>Modification</u> Change
0.1	N/A	Draft agreed for June 2019 consultation
0.2	XX 2020	Draft agreed for November 2020 re-baselining
0.3	N/A	Updated draft for Spring 2021 Switching Consultation
1.0	18 July 2022	Switching SCR Modification R0041 R0045
1.1	4 November 2022	R0036
2.0	30 June 2023	R0030
2.1	03 November 2023	R0138
2.2	23 August 2024	R0121
2.3	06 September 2024	R0192
3.0	22 September 2025	R0209
3.1	07 November 2025	R0205, R0215, R0279
<u>4.0</u>	<u>Code Manager Licence Commencement Date</u>	<u>Minor housekeeping changes consistent with nomenclature of Code Reform and Code Manager Licence</u>



Section A: General Obligations

1 Introduction

- 1.1. This [REC Schedule](#) sets out the rules and operational procedures for resolving [Consumer](#)-facing problems that may impact a [Consumer](#)'s experience of switching or the accuracy of their energy bill. The operational procedures cover [Consumer](#)-facing problems that have been identified by an [Energy Supplier](#) or notified by a [Consumer](#) or a third party.
- 1.2. The objective of this [REC Schedule](#) is to provide the framework for:
 - (a) affected parties to cooperate in a timely manner to resolve the problems covered by this [REC Schedule](#) with the minimum negative impact on [Consumers](#); and
 - (b) resolving disputed or delayed resolutions between [Energy Suppliers](#).
- 1.3. All messages, initiations and responses sent between [Market Participants](#) under this [REC Schedule](#) shall be structured and communicated in accordance with the [Data Specification](#).
- 1.4. Each [Party](#) shall ensure that all rejected messages are monitored. Where rejection messages are received, the recipient shall identify the cause of the rejection and ensure appropriate actions are taken in accordance with the relevant process and the [Data Specification](#).
- 1.5. Each [Energy Supplier](#) (excluding Non-Domestic [Gas Suppliers](#)) and each [Distribution Network Operator](#) shall ensure that, where personal data relating to a [Consumer](#) is exchanged in any operational or escalation communications referred to within this [REC Schedule](#) and where that personal data is not required by this [REC Schedule](#) to be sent via another secure means, that such personal data is sent using the [Secure Data Exchange Service](#) ([SDES](#)).

2 [Consumer](#) Principles and Outcomes

- 2.1. If a [Consumer](#) identifies or suspects a problem with their energy supply, they may contact any of the [Energy Suppliers](#) involved for a resolution. The [Energy Supplier](#) contacted by a [Consumer](#) or a third party shall take the necessary steps to investigate the problem in a timely manner, and where applicable, initiate a resolution on the [Consumer](#)'s behalf (that [Energy Supplier](#) shall be the [Initiating Supplier](#)).
- 2.2. Before initiating any of the processes in this [REC Schedule](#) involving one or more other affected [Energy Suppliers](#), the [Energy Supplier](#) shall check whether another of the affected [Energy Suppliers](#) has already initiated the relevant process, to avoid dual initiation.

- 2.3. All affected [Energy Supplier](#)s (the [Initiating Supplier](#) and [Associated Supplier](#)(s)) and any third parties as specified in this [REC Schedule](#), shall work together to ensure each problem is investigated and resolved efficiently and effectively with minimal negative impact to [Consumers](#).
- 2.4. Each [Energy Supplier](#) shall follow the process set out in this [REC Schedule](#) to resolve a problem, unless an alternative resolution process is agreed between the relevant [Energy Suppliers](#) on a bilateral basis. Such alternative processes may only be made where in all reasonable likelihood they will facilitate a better outcome for the impacted [Consumer](#)(s).
- 2.5. When resolving a problem, each affected [Energy Supplier](#) shall:
- (a) consider which [Energy Supplier](#) the [Consumer](#) believes they have an [Energy Contract](#) with;
 - (b) not use the resolution of an issue as an opportunity to enter into a new [Energy Contract](#) with the [Consumer](#); and
 - (c) take into account the needs of [Vulnerable Consumers](#).
- 2.6. Each [Energy Supplier](#) shall ensure that:
- (a) all [Consumer](#) queries are received, handled and processed in an efficient and timely manner;
 - (b) all information is complete, accurate, and not misleading;
 - (c) [Consumers](#) are only charged once for each unit of energy consumed; and
 - (d) any over payment made by the [Consumer](#) during the period of the problem shall be refunded in a timely manner and that the approach to recovering any under-payment is proportionate.
- 2.7. As soon as reasonably practicable after the initial contact, and to the extent relevant, the [Initiating Supplier](#) shall provide the [Consumer](#) with sufficient information, in a form that takes account of the needs of the [Consumer](#), to enable them to understand:
- (a) what has happened, what action will be taken to resolve the problem, and indicative timescales for resolution;
 - (b) how the [Consumer](#) will be kept informed of progress towards resolution, including who they should contact if they have any further questions or concerns; and
 - (c) on request, how complaints will be resolved and, where appropriate,

compensation claims will be dealt with

- 2.8. Where applicable, compensation claims shall be dealt with in accordance with the Electricity and Gas Standards of ~~Performance~~ Suppliers) Regulations 2015.
- 2.9. Taking into account the timescales specified in the interface table for each problem resolution, the [Initiating Supplier](#) (and, where applicable, the [Associated Supplier\(s\)](#)) shall provide prompt confirmation in writing to the [Consumer](#) that a problem has been resolved. If no problem was identified, the [Initiating Supplier](#) shall promptly provide the [Consumer](#) with a statement of the outcome of their investigation.
- 2.10. Each [Energy Supplier](#) shall ensure that any incorrect data associated with the [Consumer](#) and/or their premises (including incorrect [Settlement](#) data) is corrected and updated in the [Central Switching Service](#), [Gas Central Data Service](#), [Supplier Meter Registration Service](#) and / or [Electricity Registration Data Service](#) (as applicable), in a timely manner to ensure that these do not cause any detriment to the [Consumer](#) in the future.
- 2.11. The [CSS Provider](#) and each other [Switching Data Service Provider](#) shall provide reports as requested by ~~the Code Manager~~RECCo and / or the [REC Performance Assurance Board](#) to support monitoring of [Energy Suppliers'](#) performance in meeting their obligations under this [REC Schedule](#).

Gas Transporter Payments to Consumers

- 2.12. Where a [Gas Supplier](#) receives a payment from a [Gas Transporter](#) which is intended for onward transmission to a [Consumer](#), the [Gas Supplier](#) shall, within 10 [Working Days](#) of receipt, pay or set-off an equal sum in accordance with standard licence condition 19 of the [Gas Supply Licence](#).
- 2.13. Paragraph 2.12 shall apply whether the payment is received directly from the [Gas Transporter](#) or via the [Shipper](#) and shall apply whether the payment is a statutory payment or a voluntary payment.

3 Escalation of Delayed and Disputed Resolutions

- 3.1. The escalation procedures in this Paragraph 3 shall only apply to [Parties](#) where they are mandated under this [REC Schedule](#) to comply with the relevant operational procedures in Sections B to G, unless explicitly provided for in another [REC Schedule](#).
- 3.2. In accordance with Clause 24 of the main body of this [Code](#), each [Party](#) shall provide [Operational Contacts](#) to ~~the Code Manager~~RECCo, to support resolution of issues covered by this [REC Schedule](#). This must include registering appropriate [Secure Data Exchange Portal \(SDEP\)](#) Users with permissions to view and respond to escalations for delayed or disputed problem resolutions where messages are sent

using the [Secure Data Exchange Service](#).

- 3.3. Each [Energy Supplier](#) shall provide a telephone service for managing operational and escalation queries from other [Energy Suppliers](#). As a minimum, the telephone service shall be operated within [Working Hours](#). This shall include all operational issues covered by this [REC Schedule](#) and queries relating to Annulments.
- 3.4. Each [Energy Supplier](#) shall progress problem resolution without undue delay and shall take all reasonable steps to come to an agreement that respects the [Consumer's](#) reasonable requirements.
- 3.5. Each [Energy Supplier](#) shall ensure that they keep evidence for at least 12 months for any decisions that they make in respect to the resolution of problems under this [REC Schedule](#).
- 3.6. If an [Energy Supplier](#) involved in resolving a problem has not received a response from another [Energy Supplier](#) within the maximum timescale for any given step described in an interface table for the specific problem resolution (or within the required timescale of any bilateral process as described in Paragraph 2.4), then the [Energy Supplier](#) may escalate the issue to the [Operational Contact](#) of the other [Energy Supplier](#), using the relevant Escalation Process Type in [SDEP](#) if appropriate.
- 3.7. If a response has been received in respect of a problem covered by this [REC Schedule](#), but an [Energy Supplier](#) is not satisfied with the response received or is otherwise not satisfied with the steps taken to resolve the problem, then the [Energy Supplier](#) may escalate the issue to the [Operational Contact](#) of the other [Energy Supplier\(s\)](#) involved, using the relevant Escalation Process Type in [SDEP](#) if appropriate.
- 3.8. If in the resolution of an [Erroneous Switch](#), the [Losing Supplier](#) has not re-registered the [Registrable Measurement Point \(RMP\)](#) within the timescales set out in the relevant interface table then the other [Energy Supplier](#) may escalate the issue to the [Operational Contact](#) of the [Losing Supplier](#), using [Market Message PT0020 Erroneous Transfer Re-registration Escalation \(Elec\)](#) and [PT0035 Erroneous Transfer Re-registration Escalation \(Gas\)](#).
- 3.9. If the dispute is not resolved within five [Working Days](#) after the issue is escalated under Paragraph 3.6, 3.7 or 3.8, the affected [Energy Supplier](#) may escalate the issue to the [Contract Manager](#). If no resolution can be reached within five [Working Days](#) after the issue is escalated to the [Contract Manager](#), then the affected [Energy Supplier](#) may escalate the issue to ~~RECCo the Code Manager~~ for consideration. Where appropriate, ~~the RECCo Code Manager~~ may escalate the issue to the [REC Performance Assurance Board](#) for review.
- 3.10. The table below provides a summary of the escalation processes for how delayed or

disputed resolutions shall be managed between [Energy Suppliers](#).

Escalation Route	Pre-Conditions
Operational Contact	Response not received, or other required step not taken, within the timescales provided for in this REC Schedule , or such response or step is not satisfactory.
Contract Manager	After five Working Days of escalating the issue to the Operational Contact .
Code Manager RECCo	The Party may notify the Code Manager RECCo after five Working Days of escalating the issue to the Contract Manager .
REC Performance Assurance Board	As agreed between the Code Manager RECCo and the REC PAB .

3.11. In addition to the other provisions of this Paragraph 3, [Energy Suppliers](#) and [Distribution Network Operators](#) should use reasonable endeavours to use the [SDEP](#) in an effective way and to resolve queries raised under processes related to any [REC Schedule](#), using the [SDEP](#), in a prompt manner.

3.12. A [Contract Manager](#) General Query [PT0031](#) (electricity) and [PT0043](#) (gas) may be raised via the [SDEP](#) by an [Energy Supplier](#) or [Distribution Network Operator](#), where a query is unresolved and all other available escalation routes (if any) have been exhausted.

Section B: [Erroneous Switch](#)

4 Description of the Problem

4.1. An [Erroneous Switch](#) occurs where a [Consumer](#) has been switched to an [Energy Supplier](#) which does not have an [Energy Contract](#) in place. An [Erroneous Switch](#) only occurs once the [Registration Status](#) of the erroneous [Energy Supplier](#)'s [Registration](#) has become [Secured Active](#) or [Active](#).

4.2. The [Energy Supplier](#) that is notified of, or otherwise identifies, a potential [Erroneous Switch](#) (which will be the [Initiating Supplier](#)) shall initiate a resolution process to switch the [RMP](#)'s [Registration](#) back to the [Energy Supplier](#) that holds the [Energy Contract](#) for the [RMP](#). The [Initiating Supplier](#) shall do this by sending an [Initial Request](#) to the [Associated Supplier](#). The [Initiating Supplier](#) shall use the [Enquiry Services](#) to establish the identity of the [Associated Supplier](#).

4.3. Where a proposed [Switch](#) which would become an [Erroneous Switch](#) is identified before the [Gaining Supplier](#)'s [Registration Status](#) becomes [Secured Active](#) or [Active](#), then the [Gaining Supplier](#) or [Losing Supplier](#) (whichever first becomes aware) shall take the necessary steps to prevent the [Switch](#), for example by sending a [Withdrawal Request](#) or [Annulment Request](#) (as applicable) in accordance with the [Registration](#)

Services Schedule.

- 4.4. The procedure in this Section B may also be used in circumstances where the [Gaining Supplier](#) agrees to return a [Consumer](#) to the [Losing Supplier](#) on a goodwill basis (referred to as a [Customer Service Returner](#)). However, for reporting purposes, a [Customer Service Returner](#) is not categorised as an [Erroneous Switch](#).
- 4.5. This Section B shall only be used in the period of 24 months following the suspected [Erroneous Switch](#). Beyond this point, [Energy Supplier](#)s shall seek to agree bilaterally how to treat a potential [Erroneous Switch](#).
- 4.6. Where an [Erroneous Switch](#) has taken place which involves more than two [Energy Supplier](#)s, and they are in agreement that an [Erroneous Switch](#) has taken place, then the [Erroneous Switch](#) shall be resolved between the [Energy Supplier](#)s via telephone. Following this, a confirmation can be sent via the [Secure Data Exchange Portal](#) (SDEP) to all involved [Energy Supplier](#)s using [Market Message PT0047 Erroneous Transfers General Query \(Elec\)](#) and [PT0048 Erroneous Transfers General Query \(Gas\)](#).
- 4.7. In the event of an [Erroneous Switch](#) where the [Losing Supplier](#) ceases to trade prior to being re-registered as the [Registered Supplier](#) in accordance with Paragraph 6.9.3, then the [Gaining Supplier](#) shall cancel the [Erroneous Switch](#) request.
- 4.8. In the event of an [Erroneous Switch](#) where the [Gaining Supplier](#) ceases to trade before the [Erroneous Switch](#) has been resolved, then the [Losing Supplier](#) shall cancel the [Erroneous Switch](#) request and discuss options with the [Consumer](#) (including the [Losing Supplier](#)'s re-registration as the [Registered Supplier](#)).
- 4.9. In the event of an [Erroneous Switch](#) where a [Change of Occupier](#) occurs such that the [Gaining Supplier](#) has entered into an [Energy Contract](#) with the new occupier (including by way of a deemed contract) before the [Losing Supplier](#) has been re-registered as the [Registered Supplier](#) in accordance with Paragraph 6.9.3, then the [Gaining Supplier](#) may cancel the [Erroneous Switch](#) request.

5 Resolution Outcomes

- 5.1. In addition to the relevant requirements of Paragraph 2, the resolution of [Erroneous Switch](#)es needs to deliver the following minimum outcomes to be considered complete:
 - (a) the [Energy Supplier](#) that holds the [Energy Contract](#) has requested to be re-registered as the [Registered Supplier](#) on the [CSS](#) and its [Registration Status](#) is [Secured Active](#) or [Active](#); and
 - (b) in circumstances where a [Gaining Supplier](#) has switched the wrong [Consumer](#),

the [Consumer](#) that is waiting to be switched must be informed of the problem and agree (where they wish to do so) a new [Supply Effective From Date](#).

- (c) For the avoidance of the doubt the [Gaining Supplier](#) must not bill the consumer for any energy taken over any period for which they have been erroneously switched.

5.2. If the [Gaining Supplier](#) identifies that an [Erroneous Switch](#) has occurred for a [Consumer](#) that the [Losing Supplier](#) has already re-registered or is in the process of re-registering, the [Erroneous Switch](#) request takes precedence. This means that a [Losing Supplier](#) cannot reject an [Erroneous Switch](#) request if they are already in the process of re-registering. In this situation, the [Losing Supplier](#) shall accept responsibility for billing during the period that the [Consumer](#) was being supplied by the [Gaining Supplier](#), although the decision on whether to bill the [Consumer](#) for any energy taken over this period will remain at the discretion of the [Losing Supplier](#).

5.3. The [Gaining Supplier](#) shall take reasonable steps to stop collecting data from the meter once a potential [Erroneous Switch](#) has been identified. Once both [Energy Suppliers](#) have agreed that an [Erroneous Switch](#) has taken place, the [Gaining Supplier](#) shall delete any data that it may have collected from the meter during the period for which it was erroneously registered.

5.4. In addition to the resolution of the [Erroneous Switch](#), each [Gaining Supplier](#) also has to comply with the [Guaranteed Standards of Performance](#) (GSOP) Regulation 6ZB and make a payment to the [Consumer](#) where the standard is failed. However, the [Gaining Supplier](#) may not always have the [Consumer](#) details to make the payment. The steps detailed below allow the [Gaining Supplier](#) to request the information from the [Losing Supplier](#):

- (a) The [Gaining Supplier](#) shall send a [Market Message](#), via the [SDEP](#), using [Market Message PT0061 - Erroneous Transfer GSoP Payment Customer Details General Query \(Gas\)](#) and [PT0062 - Erroneous Transfer GSoP Payment Customer Details General Query \(Elec\)](#), to the [Losing Supplier](#) providing the [MPAN](#) for the relevant [Metering Point](#).
- (b) Within 5 [Working Days](#) the [Losing Supplier](#) shall respond via the [SDEP](#) query, either providing the [Consumer](#) name, where available; or providing confirmation that no details are available (i.e. the site is vacant or a [Change of Occupier](#) has occurred since the [Losing Supplier](#)'s supply period so new details are not available). In this latter instance the [Losing Supplier](#) shall provide any additional information it has available to help the [Gaining Supplier](#) identify the [Consumer](#).

5.5. The process in Paragraph 5.4 only applies where:

- (a) the supply relates to a [Domestic Premises](#) so the [Consumer](#) is entitled to

[Guaranteed Standards of Performance](#) (GSOP) Regulation 6ZB compensation payment;

- (b) an [Erroneous Switch](#) has been agreed between [Energy Suppliers](#) in accordance with this Section B;
- (c) the electricity [D0301](#) ([Erroneous Transfer Communication](#)) / gas [RET Flow Market Message](#) does not contain the [Consumer](#)'s name;
- (d) the electricity Reason for Return ([J1671](#)) [Data Item](#) is D (Incorrect [MPAN](#) Selected) / gas Reason for Return ([DI40212](#)) [Data Item](#) is I (Incorrect MPXN Selected) in the agreed [D0301](#) / [RET Flow Market Message](#); and
- (e) the [Gaining Supplier](#)'s [Supply Effective From Date](#) is on or after 1st May 2020.

5.6. If an [Erroneous Switch](#) is cancelled in accordance with Paragraphs 4.7 to 4.9, the [Gaining Supplier](#) will remain responsible for the [RMP](#).

5.7. The valid cancellation of an [Erroneous Switch](#) in accordance with Paragraphs 4.7 to 4.9 does not determine whether compliance with the [Guaranteed Standards of Performance](#) (or any other requirement of [Law](#) or [Energy Licences](#)) has been achieved, or whether payments or damages are due to the [Consumer](#) as a result. Each [Party](#) shall make its own assessment of compliance with any statutory provision required outside of this [Code](#).

5.8. Where an [Erroneous Switch](#) is cancelled in accordance with Paragraphs 4.7 to 4.9, the [Energy Supplier](#) who cancels the [Erroneous Switch](#) shall write to the [Consumer](#) within 5 [Working Days](#) setting out:

- (a) the reasons for the cancellation; and
- (b) the [Consumer](#)'s rights to [Switch](#) to another [Energy Supplier](#).

6 Resolution Process

6.1. Prior to sending an [Initial Request](#), the [Energy Supplier](#) shall confirm if an electricity [RMP](#) is associated to a [Green Deal Plan](#). If so, the [Electricity Supplier](#) shall comply with the relevant requirements in the [Green Deal Arrangements Schedule](#).

6.2. The [Initiating Supplier](#) should issue a separate [Initial Request Market Message](#) in relation to each impacted [RMP](#), even in the case of electricity [Related Metering Points](#). Where it is identified through this process that the [Related Metering Points](#) have been erroneously linked, the [Registered Supplier](#) shall correct the [Related Metering Point](#) relationship before the [Switch Request](#) is initiated to resolve the [Erroneous Switch](#).



- 6.3. If two or more [Energy Suppliers](#) have sent an [Initial Request](#) in relation to the same problem under this Section B (referred to as a [Dual Initiation](#)), the following actions shall be taken:
- (a) if a [Dual Initiation](#) has taken place on the same day - the [Gaining Supplier](#) shall be the [Initiating Supplier](#) and shall reject the [Initial Request](#) from the [Losing Supplier](#) (which shall become the [Associated Supplier](#)), and within the rejection reason the [Gaining Supplier](#) shall state that a [Dual Initiation](#) has occurred, and that it will take the role of the [Initiating Supplier](#); or
 - (b) if a [Dual Initiation](#) has not taken place on the same day - the [Energy Supplier](#) which sent the earlier [Initial Request](#) shall be the [Initiating Supplier](#) and shall reject the [Initial Request](#) from the other [Energy Supplier](#) (which shall become the [Associated Supplier](#)). The [Energy Supplier](#) which sent the earlier [Initial Request](#) shall use a rejection code to state that a [Dual Initiation](#) has occurred, and that it will take the role of the [Initiating Supplier](#).
- 6.4. Upon receipt of the [Initial Request](#) from the [Initiating Supplier](#), the [Associated Supplier](#) shall either accept or reject the [Initial Request](#). Where the [Initiating Supplier](#) is the [Gaining Supplier](#), the [Associated Supplier](#) may only reject the [Initial Request](#) for an [Erroneous Switch](#) in circumstances where:
- (a) the [Associated Supplier](#) is not the [Losing Supplier](#) and has been contacted in error;
 - (b) the [Consumer](#) has decided to cancel the [Erroneous Switch](#); or
 - (c) a [Dual Initiation](#) has taken place in accordance with Paragraph 6.2.
- 6.5. The following factors shall not be used as a reason for rejecting an [Initial Request](#) regarding an [Erroneous Switch](#):
- (a) disparity between the [Losing Supplier](#) and [Gaining Supplier](#) records of the [Meter Serial Numbers](#);
 - (b) disparity between the [Losing Supplier](#) and [Gaining Supplier](#) records of the [Consumer](#)'s name;
 - (c) missing data flows, for example a loss notification has not been received in relation to a [Switch](#); or
 - (d) no valid [Energy Contract](#).
- 6.6. Following receipt by the [Initiating Supplier](#) of a rejection response where the [Associated Supplier](#) responds that it is not the [Losing Supplier](#), the [Initiating Supplier](#)

shall establish the identity of the correct [Losing Supplier](#) and re-send the [Initial Request](#) accordingly.

- 6.7. If the [Associated Supplier](#) receives a further [Initial Request](#) for the same [RMP](#) from the same [Initiating Supplier](#), and the request is still believed to be invalid, prior to sending a second rejection response, the [Associated Supplier](#) shall contact the [Initiating Supplier](#) by telephone to discuss the [Initial Request](#) and the reason for rejection. The [Associated Supplier](#) shall seek to come to a conclusion with the [Initiating Supplier](#) as to whether the [Initial Request](#) is valid or invalid. Where the [Associated Supplier](#) continues to dispute the [Initial Request](#), the escalation process in Paragraph 3, using [Market Message PT0013 Erroneous Transfer Escalation \(Elec\)](#) and [PT0034 Erroneous Transfer Escalation \(Gas\)](#), shall apply.
- 6.8. Where the [Associated Supplier](#) agrees that the [Initial Request](#) is valid, the [Associated Supplier](#) shall accept the [Initial Request](#) and the [Losing Supplier](#) shall re-register the [RMP](#).
- 6.8A [Energy Suppliers](#) may use the [SDEP](#) to raise queries and otherwise securely exchange information related to [Erroneous Switches](#), using [Market Messages PT0047 Erroneous Transfers General Query \(Elec\)](#) and [PT0048 Erroneous Transfers General Query \(Gas\)](#).
- 6.8B For Advanced Electricity Meters, once the [Losing Supplier](#) has re-registered the [RMP](#), the [Gaining Supplier](#) must provide the [Losing Supplier](#) with the [Half-Hourly](#) consumption data held (actual or estimated) for the period they were the [Registered Supplier](#) within 5 [Working Days](#) of the [Erroneous Switch](#) being agreed in accordance with 6.9.11. This must be provided using [Market Messages PT0047 Erroneous Transfers General Query \(Elec\)](#) within [SDEP](#) using the Advanced Meter Half-Hourly Consumption Data Template ~~provided by the Code Manager in published on the REC Portal at: <https://recportal.co.uk/operational-documents>~~ [Appendix 4](#).
- 6.8C In relation to 6.8B, where the [Gaining Supplier](#) has used the reverse migration process and does not have [Half-Hourly](#) consumption data to provide, the [Gaining Supplier](#) must provide the [Losing Supplier](#) with any register readings held for the period they were the [Registered Supplier](#).
- 6.9. The following interface table sets out the process and maximum timelines for resolving an [Erroneous Switch](#).

Ref	When	Action	From	To	Interface	Means
6.9.1	No later than the end of the: a) 2nd WD if it is the Losing Supplier; or b) 8th WD if it is the Gaining Supplier, of initial Consumer contact or of receiving information from a third party, indicating a potential Erroneous Switch.	Send Initial Request .	Initiating Supplier	Associated Supplier	For Gas RMP(s) RET Flow For Electricity RMP(s) Erroneous Transfer Communication (D0301)	DTN
6.9.2	No later than the end of the: a) 2nd WD if it is the Losing Supplier; or b) 8th WD if it is the Gaining Supplier, of receiving an Initial Request.	Return the Initial Request with confirmation of: a) <i>Acceptance</i> – proceed to 6.9.3; or b) <i>Rejection</i> – proceed to 6.9.6.	Associated Supplier	Initiating Supplier	For Gas RMP(s) RET Flow Erroneous Transfer Communication (D0301)	DTN
6.9.3	Following 6.9.2 and within 2 WDs , where the Initial Request is accepted by the Initiating Supplier and Associated Supplier .	Send a Valid Switch Request to re-register the erroneously switched RMP(s) on the CSS with the Erroneous Switch Flag indicator set to true.	Losing Supplier	CSS Provider	As set out in the Registration Services Schedule	CSS API
6.9.4	Following 6.9.3 and within the timings defined in the Registration Services	Progress the Switch Request as specified in the Registration Services Schedule .	CSS Provider		As set out in the Registration Services Schedule	



	Schedule.					
6.9.5	Following 6.9.4, but no later than 20 WDs of an Erroneous Switch first being suspected (either through initial Consumer contact or an Energy Supplier otherwise becoming aware that an Erroneous Switch may have occurred).	Provide written confirmation to the Consumer that resolution has been agreed and they will be returned to their Losing Supplier .	Initiating Supplier	Consumer		Not Defined
6.9.6	Following 6.9.2, if the Initial Request was rejected by the Associated Supplier .	Correct the request and restart the process at 6.9.1, or progress to 6.9.7	Initiating Supplier		Internal process	N/A
6.9.7	Following 6.9.2, if the Initiating Supplier disagrees with the rejection response.	Follow the escalation procedure in Paragraph 3.	Initiating Supplier		For Electricity RMPs PT0013 Erroneous Transfers Escalation (Elec) For Gas RMPs PT0034 Erroneous Transfers Escalation (Gas)	SDEP
6.9.8	As soon as reasonably practicable following 6.9.2, if the Initiating Supplier agrees with the rejection response.	Provide written communication to the Consumer informing them that the Erroneous Switch request has been rejected and the reasons for the rejection.	Initiating Supplier	Consumer		Not defined
6.9.9	Where the criteria in Paragraphs 4.7 to 4.9 applies	Send an Erroneous Switch cancellation request	Cancelling Energy Supplier	Other Energy Supplier	For Gas RMP(s) RET Flow	

					For Electricity RMP(s) Erroneous Transfer Communication	
6.9.10	Within 5 Working Days of 6.9.9	Provide written communication to the Consumer as per Paragraph 5.8.	Cancelling Energy Supplier	Consumer		Not Defined
6.9.11	For Advanced Electricity Meters, as soon as reasonably practicable following 6.9.4, but no later than 5 Working Days .	Provide Half-Hourly consumption data for the period the Gaining Supplier were the Registered Supplier .	Gaining Supplier	Losing Supplier	PT0047 Erroneous Transfers General Query (Elec) , in CSV file in the format set out in the annex to this Section B.)	SDEP

Section C: [Switch Meter Reading](#) Problems

7 Description of the Problem

- 7.1. As part of a [Switch](#), a [Switch Meter Reading](#) must be determined to ensure that the [Consumer](#) receives an accurate opening and closing bill. The [Switch Meter Reading](#) will also establish a single point at which responsibility for the consumption at the [RMP](#) transfers from the [Losing Supplier](#) to the [Gaining Supplier](#).
- 7.2. The arrangements for obtaining gas and electricity [Switch Meter Reading](#)s are detailed in the [UNC/IGT UNC](#) and [BSC](#) respectively.
- 7.3. The resolution of [Switch Meter Reading](#) problems covers the following scenarios:
- (a) the proposed [Switch Meter Reading](#) is disputed by the [Consumer](#), [Losing Supplier](#) or [Gaining Supplier](#) (referred to as a [Disputed Switch Meter Reading](#)), and 12 months have not passed since the [Supply Effective From Date](#) (or later, where the [Energy Suppliers](#) have bilaterally agreed to follow this process);
 - (b) for a gas [RMP](#), where an actual or estimated [Switch Meter Reading](#) has not been received from the gas

[Central Data Service Provider \(CDSP\)](#) by the [Losing Supplier](#) (via the [Shipper](#)) within 15 [Working Days](#) of its [Supply Effective Through Date](#), or by the [Gaining Supplier](#) within 17 [Working Days](#) of its [Supply Effective From Date](#);

- (c) for an [MHHS Metering Point](#) where supply is measured by a [Traditional Metering Asset](#), where a [Customer Own Read](#) or estimated [Switch Meter Reading](#) has not been received by the [Losing Supplier](#) or [Gaining Supplier](#) within 10 [Working Days](#) of the [Gaining Supplier's Supply Effective From Date](#);
- (d) for an electricity [MHHS Metering Point](#) where supply is measured by a [Smart Metering Asset](#), where the [Losing Supplier](#) or [Gaining Supplier](#) has been unable to retrieve actual data from the [Smart Metering Asset](#) and has not received an actual or estimated [Switch Meter Reading](#) from the Losing [Smart Data Service](#) within 10 [Working Days](#) of the [Gaining Supplier's Supply Effective From Date](#);
- (e) for a [Non-MHHS Metering Point](#), where supply is measured by a meter that is not an [Enrolled Smart Meter](#), where an actual or estimated [Switch Meter Reading](#) has not been received from the [Data Collector](#) by the [Losing Supplier](#) within 15 [Working Days](#) of its [Supply Effective Through Date](#), or by the [Gaining Supplier](#) within 17 [Working Days](#) of its [Supply Effective From Date](#); or
- (f) for a [Non-MHHS Metering Point](#), where supply is measured by an [Enrolled Smart Meter](#) where the [Losing Supplier](#) has been able to obtain a [Meter Reading](#) from the [Enrolled Smart Meter](#) but has not received a proposed [Switch Meter Reading](#) from the [Gaining Supplier](#) within 10 [Working Days](#) of the [Gaining Supplier's Supply Effective From Date](#).

7.4. For [MHHS Metering Points](#), in the event that the [Gaining Supplier](#) requires [Meter Register Readings](#) for [Smart Metering Assets](#), they may use the last Register Reading ([J0040](#)) provided via the Notification of Losing Supplier Information ([D0311](#)) [Market Message](#). Where this data is not available, the Register Readings should be requested from the [Losing Supplier](#) via the [SDEP](#).

8 Resolution Outcomes

8.1. In addition to the relevant requirements in Paragraph 2, the resolution of [Switch Meter Reading](#) problems needs to deliver the following minimum outcomes to be considered complete:

- (a) the [Gaining Supplier](#) and [Losing Supplier](#) have respectively opened and closed the [Consumer's](#) account details on the same [Switch Meter Reading](#) (or agreed otherwise);
- (b) where appropriate, the [Consumer](#) has been sent amended opening and / or closing bills covering the full disputed period. [Consumer](#) billing should be

corrected for the full period of erroneous data, regardless of whether an equivalent correction is applied within [Settlements](#): and

- (c) both the [Gaining Supplier](#) and [Losing Supplier](#) have received a [Switch Meter Reading](#) in accordance with the [UNC](#) / [IGT UNC](#) or [BSC](#) (as applicable). In the case of [Gas Suppliers](#), the [Switch Meter Reading](#) will be received via the [Shipper](#). In the case of an electricity [Switch Meter Reading](#) that has been subject to final reconciliation in [Settlement](#), the [Gaining Supplier](#) and [Losing Supplier](#) shall meet the outcomes in 8.1(a) and 8.1(b) regardless of whether the [Switch Meter Reading](#) is capable of amendment with their [Data Service Agent](#) or [Data Collector](#), as applicable.

9 Resolution Process

- 9.1. The procedure in this Section C shall only be initiated where one of the scenarios described in Paragraph 7.3 applies. The procedure in this Section C shall not be used in relation to a [RMP](#) where an [Erroneous Switch](#) is in progress.
- 9.2. Where the requirements of Paragraph 9.1 are met, the [Energy Supplier](#) may initiate the procedure in this [REC Schedule](#) with the objective to:
 - (a) agree a [Switch Meter Reading](#) where no actual or estimated [Switch Meter Reading](#) has been obtained; or
 - (b) agree an alternative [Switch Meter Reading](#) where the original [Switch Meter Reading](#) is being disputed.
- 9.3. Where the [Consumer](#) is disputing the [Switch Meter Reading](#), the [Energy Supplier](#) shall endeavour to reach an agreement with the [Consumer](#) without invoking this disputes process.
- 9.4. The [Energy Supplier](#) contacted by the [Consumer](#) shall consider the specific circumstances as detailed below:
 - (a) where the difference between the [Energy Supplier](#)'s view of consumption and that derived from the initial [Switch Meter Reading](#) is 1,200 kWh or less for a gas [RMP](#) or 250 kWh or less for an electricity [RMP](#), then the [Energy Supplier](#) shall not dispute the [Switch Meter Reading](#) unless the [Consumer](#) specifically requests a new [Switch Meter Reading](#), but shall instead attempt to resolve the dispute with an accommodation (e.g. cash allowance to the [Consumer](#)), thus retaining the initial proposed [Switch Meter Reading](#), so that no further action is then required; or
 - (b) where the [Consumer](#) is unwilling to accept an accommodation, or the difference between the [Energy Supplier](#)'s view of consumption and that derived from the

[Switch Meter Reading](#) is more than 1,200 kWh for a gas [RMP](#) or more than 250 kWh for an electricity [RMP](#), then the [Energy Supplier](#) shall initiate a dispute.

9.5. The [Consumer](#) is not obliged to provide information on the identity of either their [Gaining Supplier](#) or [Losing Supplier](#). Therefore, the [Initiating Supplier](#) shall use the [Enquiry Services](#) to establish the identity of the [Associated Supplier](#).

9.6. For gas [Supply Meter Points](#), each [Gas Supplier](#) shall ensure they use the active [Settlement](#) registers of the meter as part of the procedure for resolving missing [Switch Meter Readings](#) under this Section C.

9.6A For [MHHS Metering Points](#), each [Electricity Supplier](#) shall ensure they use the [Cumulative Register Reading](#) for [Smart Metering Assets](#) and the [Meter Register Readings](#) for [Traditional Metering Assets](#), as part of the procedure for resolving missing [Switch Meter Readings](#) under this Section C. This does not preclude the [Electricity Suppliers](#) from sharing [Meter Register Readings](#) for [Smart Metering Assets](#) to support resolution of [Consumer](#) billing issues.

9.6B For [Non-MHHS Metering Points](#) each [Electricity Supplier](#) shall ensure they use the active [Settlement](#) registers of the meter as part of the procedure for resolving missing [Switch Meter Readings](#) under this Section C.

9.7. If two or more [Energy Suppliers](#) have sent an [Initial Request](#) in relation to the same problem under this Section C (referred to as a [Dual Initiation](#)), then the [Gaining Supplier's](#) [Initial Request](#) shall take precedence (and it will take on the role of the [Initiating Supplier](#)).

9.8. When responding to the [Initial Request](#), the [Associated Supplier](#) shall consider the specific circumstances and determine whether a more suitable [Switch Meter Reading](#) is available. The [Associated Supplier](#) shall either accept the proposed read, negotiate the outcome by proposing a more suitable reading, or request an [Actual Meter Reading](#). Where an alternative read is provided justification should be provided.

9.9. Following agreement of the [Switch Meter Reading](#):

- (a) for a gas [RMP](#), the [Gaining Supplier](#) shall submit the agreed [Switch Meter Reading](#) to the gas [CDSP](#), via its [Shipper](#), in accordance with the [UNC](#) / [IGT UNC](#); or
- (b) for an [MHHS Metering Point](#), both the [Gaining Supplier](#) and [Losing Supplier](#) shall submit the agreed [Switch Meter Reading](#) to their respective [Data Services](#) in accordance with the [BSC](#). Suppliers shall correct [Consumer](#) billing to reflect the agreed [Switch Meter Reading](#) even if it is not possible to amend the data in [Settlement](#).



- (c) for a [Non-MHHS Metering Point](#), where supply is measured by a meter that is not an [Enrolled Smart Meter](#), the [Gaining Supplier](#) shall submit the agreed [Switch Meter Reading](#) to its [Data Collector](#), in accordance with the [BSC](#); or
 - (d) for a [Non-MHHS Metering Point](#), where supply is measured by a meter that is an [Enrolled Smart Meter](#), both the [Gaining Supplier](#) and [Losing Supplier](#) shall submit the agreed [Switch Meter Reading](#) to their respective [Data Collector](#) in accordance with the [BSC](#).
- 9.10. If the [Switch Meter Reading](#) submitted under Paragraph 9.9 is not accepted under the [UNC](#) / [IGT UNC](#) or [BSC](#) (as applicable), then the [Energy Suppliers](#) may either initiate the process described in Paragraph 3, using [Market Messages PT0012 Disputed Meter Readings Escalation \(Elec\)](#) and [PT0033 Disputed Meter Readings Escalation \(Gas\)](#) or agree between themselves that the agreed [Switch Meter Reading](#) shall be used only for the purposes of [Consumer](#) billing.
- 9.10A Where personal data relating to a [Consumer](#) is exchanged in an operational communication in accordance with Paragraph 1.5, or [Energy Suppliers](#) need to raise a query using the [SDEP](#), they should use the appropriate [Market Message](#) from [PT0045 Disputed Meter Readings General Query \(Elec\)](#), [PT0046 Disputed Meter Readings General Query \(Gas\)](#), [PT0069 Missing Read General Query \(Elec\)](#) and [PT0070 Missing Read General Query \(Gas\)](#).
- 9.11. The interface table below sets out the process and maximum timelines for resolving [Switch Meter Reading](#) problems. If any steps are not completed in the timeline described, or are not completed satisfactorily, then the [Energy Suppliers](#) may initiate the escalation process described in Paragraph 3 using the appropriate [Market Messages](#) from [PT0012 Disputed Meter Readings Escalation \(Elec\)](#), [PT0033 Disputed Meter Readings Escalation \(Gas\)](#), [PT0071 Missing Read Escalation \(Electricity\)](#) and [PT0072 Missing Meter Reading Escalation \(Gas\)](#).

Ref	When	Action	From	To	Interface	Means
9.11.1	Within 5 WDs of either: a) a Switch Meter Reading being disputed; or b) a Switch Meter Reading not being obtained.	Send an Initial Request to: • agree a Switch Meter Reading where no actual or estimated Switch Meter Reading has been obtained; or • agree an alternative Switch Meter Reading where the original Switch Meter Reading is being disputed.	Initiating Supplier	Associated Supplier	For Gas RMP(s) SAR Flow (Initial Request) For Electricity RMP(s) D0300 Disputed Readings or Missing Readings on Change of Supplier	DTN
9.11.2	Following 9.11.1	Determine whether to agree the proposed read (if a proposed read was provided).	Associated Supplier		Internal process	N/A
9.11.3	Within 5 WDs of 9.11.1; where the Associated Supplier agrees the proposed read.	Provide a response accepting the proposed read and progress to 9.11.12. Where a Request was raised in regards to 9.11.1(b) (a Switch Meter Reading was not obtained) and the Switch Meter Reading has subsequently been sent, no response or further action is required.	Associated Supplier	Initiating Supplier	For Gas RMP(s) SAR Flow (Switch Meter Reading Acceptance) For Electricity RMP(s) D0300 Disputed Readings or Missing Readings on Change of Supplier	DTN
9.11.4	Within 5 WDs of 9.11.1; where the Associated Supplier does not agree the proposed read or no proposed read was sent.	Provide a response to the initial request either: a) proposing a proposed read and progressing to 9.11.5 (where a proposed read was not included	Associated Supplier	Initiating Supplier	For Gas RMP(s) SAR Flow (Initial Response) For Electricity RMP(s) D0300 Disputed Readings or Missing Readings on Change	DTN



		in the initial request); b) proposing an alternative read and progressing to 9.11.5; or c) indicating that there is no alternative read available (progress to 9.11.9).			of Supplier	
9.11.5	Following 9.11.4; where the Associated Supplier provided a proposed or alternative read.	Determine whether to agree the proposed or alternative read.	Initiating Supplier		Internal process	N/A
9.11.6	Within 5 WDs of 9.11.4; where the Initiating Supplier agrees the proposed or alternative read.	Provide a response accepting the proposed or alternative read and progress to 9.11.12.	Initiating Supplier	Associated Supplier	For Gas RMP(s) SAR Flow (Switch Meter Reading Acceptance) For Electricity RMP(s) D0300 disputed Readings or Missing Readings on Change of Supplier	DTN
9.11.7	Within 5 WDs of 9.11.4; where the Initiating Supplier does not agree the proposed or alternative read.	Contact the Associated Supplier to agree the Switch Meter Reading by telephone.	Initiating Supplier	Associated Supplier	Agreed Switch Meter Reading	Telephone
9.11.8	Within 5 WDs of 9.11.7; where a Switch Meter Reading is agreed by	Provide a response accepting the read agreed by telephone and progress to 9.11.12.	Initiating Supplier	Associated Supplier	For Gas RMP(s) SAR Flow (Telephone Read Acceptance)	DTN

	telephone.				For Electricity RMP(s) D0300 Disputed Readings or Missing Readings on Change of Supplier	
9.11.9	Where the Initiating Supplier , Associated Supplier and Consumer cannot agree a mutually acceptable Switch Meter Reading , or no alternative Switch Meter Reading is available.	Ask the Consumer to provide a Customer Own Read (if the Consumer has not already done so), instruct the Meter Reading Service to obtain an Actual Meter Reading within 10 Working Days , or obtain a meter reading directly from the Smart Metering System .	Gaining Supplier	Consumer ; or Meter Reading Service	Customer Own Read request, or Actual Meter Reading request explicitly stating that the Meter Reading is required to settle a Switch Meter Reading dispute	Not Defined
9.11.10	Within 10 WDs of 9.11.9; where the Gaining Supplier has obtained an Actual Meter Reading or a Customer Own Read .	Contact the Losing Supplier to agree the Switch Meter Reading by telephone.	Gaining Supplier	Losing Supplier	Agreed Switch Meter Reading	Telephone
9.11.11	Following 9.11.10; where a Switch Meter Reading is agreed by telephone.	Provide a response accepting the read agreed by telephone and progress to 9.11.12.	Initiating Supplier	Associated Supplier	For Gas RMP(s) SAR Flow (Telephone Read Acceptance) For Electricity RMP(s) D0300 Disputed Readings or Missing Readings on Change of Supplier	DTN



9.11.12	At any time, where the Initiating or Associated Supplier has accepted a proposed or alternative Switch Meter Reading via the data flows outlined in this table.	Submit the agreed Switch Meter Reading .	Gaining Supplier ; and Losing Supplier , where applicable	Shipper for Gas Supply Meter Points ; Data Service Agent for MHHS Metering Points ; Data Collector for Non-MHHS Metering Points	In accordance with the BSC and UNC / IGT UNC	N/A
9.11.13	For gas only, following 9.11.12 if the agreed Switch Meter Reading is not accepted by the gas CDSP .	Request replacement of the Meter Reading (s) that are preventing the agreed Switch Meter Reading from being accepted. If no agreement can be reached, follow the escalation procedure in Paragraph 3.	Gaining Supplier	Losing Supplier	PT0057 Replacement Readings General Query (Gas) PT0065 Replacement Readings Escalation (Gas)	SDEP
9.11.14	For gas only, where 9.11.13 applies and within 5 WDs .	Submit the replacement Meter Reading (s).	Losing Supplier	Shipper	In accordance with the UNC/IGT UNC	N/A

Section D: Crossed Meters

10 Description of the Problem

- 10.1. A Crossed Meter occurs where a meter installed at a Consumer's premises is associated to another RMP, which can result in the Consumer being billed for the energy consumption at another premises. This may be identified in the following scenarios:
- (a) a Consumer contacts their Energy Supplier, stating they are being charged incorrectly for their energy consumption;
 - (b) a Consumer informs their Energy Supplier that the meter details on their bill are different to those on the actual meter;
 - (c) a Consumer or Metering Equipment Manager notifies the Energy Supplier that the data associated with the meter and / or premises does not match the Energy Supplier's records; or
 - (d) the Distribution Network Operator or Gas Transporter receives a Consumer enquiry via their help desks.
- 10.2. Where a Crossed Meter is suspected, it is likely that more than one premises is affected, and that different Energy Suppliers and Meter Equipment Managers may be responsible for the different RMPs.
- 10.3. Where a Switch occurs during a Crossed Meter investigation, the Losing Supplier shall inform the Gaining Supplier of the ongoing investigation and give all reasonable assistance to the Gaining Supplier to ensure minimal disruption to the resolution.
- 10.4. Where a change of Supplier Agent(s) occurs during a Crossed Meter investigation, the Energy Supplier shall ensure that both its outgoing and incoming Supplier Agents progress the resolution of the Crossed Meter with minimum disruption to the resolution.
- 10.5. Where the Energy Supplier becomes aware that a new Consumer has moved into the premises before an identified Crossed Meter issue has been resolved, the Energy Supplier shall ensure that the new Consumer is informed, and updated as to the progress, of the relevant resolution process.

11 Resolution Outcomes

- 11.1. In addition to the relevant requirements in Paragraph 2, the resolution of a Crossed Meter needs to deliver the following minimum outcomes to be considered complete:

- (a) the [Consumer](#)'s energy consumption has been corrected, explained and reconciled using available meter reading history;
- (b) relevant [Energy Supplier](#) / [Supplier Agent](#) records have been updated; and
- (c) The [Gas Central Data Service](#), [Supplier Meter Registration Service](#) and/or [Electricity Registration Data Service](#) (as applicable) have been updated, based on the agreed dates and meter readings.

12 Resolution Process

- 12.1. Where an [Energy Supplier](#) suspects or is notified of a [Crossed Meter](#), it shall take all reasonable steps to investigate the issue in a timely and efficient manner with minimal impact to the [Consumer](#). This could include contacting the [Consumer](#), [Metering Equipment Manager](#) and [Distribution Network Operator](#) / [Gas Transporter](#), reviewing data held in the [Enquiry Services](#) or performing a site visit to confirm data associated with the meter installed at the premises.
- 12.2. [Electricity Suppliers](#) shall use the [Crossed Meter Resolution Portal](#) functionality which forms part of the [Secure Data Exchange Service](#) to support resolution of issues, unless escalation procedures in Paragraph 3 apply, in which case [Market Message PT0066 Crossed Meters Escalation \(Elec\)](#) should be sent via the [Secure Data Exchange Portal](#) (SDEP). [Gas Suppliers](#) shall use the [Secure Data Exchange Portal](#) functionality within the [Secure Data Exchange Service](#). [Gas Suppliers](#) may use the [SDEP](#) to raise queries and otherwise securely exchange information related to [Crossed Meters](#), using [Market Message PT0055 Crossed Meter General Query \(Gas\)](#).
- 12.3. If, after investigation, the [Energy Supplier](#) determines that there is no [Crossed Meter](#), then the [Energy Supplier](#) shall ensure relevant internal records and those of its [Supplier Agents](#) are accurate and updated where required. The [Energy Supplier](#) shall also ensure the [Gas Central Data Service](#), [Supplier Meter Registration Service](#) and / or [Electricity Registration Data Service](#) (as applicable) are updated where required, in accordance with the relevant standard industry process.
- 12.4. If, after investigation, the [Energy Supplier](#) identifies that a [Crossed Meter](#) has occurred, and:
 - (a) if the [Energy Supplier](#) is the [Registered Supplier](#) for all affected [RMPs](#), it shall ensure that the [Gas Central Data Service](#), [Supplier Meter Registration Service](#) and / or [Electricity Registration Data Service](#) (as applicable) are updated with any changes to data associated with the [RMP](#); or
 - (b) if the [Energy Supplier](#) determines that it is not the [Registered Supplier](#) for one or more of the affected [RMPs](#), then it shall initiate the resolution process for [Crossed](#)

Meters.

- 12.5. It is the responsibility of the [Registered Supplier](#) of each affected [RMP](#) to ensure that its [Metering Equipment Manager](#) corrects the meter data with any agreed changes and such changes are notified to the [Gas Central Data Service](#), [Supplier Meter Registration Service](#) and / or [Electricity Registration Data Service](#) (as applicable).
- 12.6. Where there is a suspected [Crossed Meter](#), [Energy Supplier](#)s shall co-ordinate the booking of appointment dates and times for site visits at [RMP](#)s which have the same [Metering Equipment Manager](#); or use reasonable endeavours to co-ordinate site visits where the [RMP](#)s are in close proximity.
- 12.7. Where a [Gas Transporter](#) or [Distribution Network Operator](#) becomes aware of a [Crossed Meter](#), it shall investigate the issue to determine all the affected [RMP](#)s within its portfolio. Following the investigation, it shall notify the [Registered Supplier](#)s of any and all affected [RMP](#)s. In the case of gas, this notification shall be communicated to the [Registered Supplier](#) via the [Shipper](#). In the case of electricity, the [DNO](#) may use [Market Message PT0077](#) Crossed Meters (DNO) General Query (Electricity) via the [SDEP](#). Each such [Registered Supplier](#) shall then investigate the issue as referred to in Paragraph 12.1. [Electricity Supplier](#)s should provide updates on the progress and conclusion of such investigations to the [DNO](#) via the [SDEP](#) General Query, if available.
- 12.8. The [Registered Supplier](#) shall confirm whether the asset details reflect the [Metering Equipment](#) installed at the location. Where the asset details are deemed to be correct, the [Registered Supplier](#) shall consider whether the MPL Address requires updating. In circumstances where a change to the MPL Address is required, the [Registered Supplier](#) shall follow the process detailed in the [Address Management Schedule](#).
- 12.9. If a [Consumer](#)'s supply has been interrupted in error whilst a [Crossed Meter](#) investigation is underway, the [Energy Supplier](#) that initiated the supply interruption shall ensure the supply is restored as soon as possible and no later than within 24 hours after the start of the interruption.



12.10. The interface table below sets out the process and maximum timelines for resolving [Crossed Meters](#). If any steps are not completed in the timeline described, or are not completed satisfactorily, then the [Energy Supplier](#)s may initiate the escalation process described in Paragraph 3 using [Market Message PT0066 Crossed Meters Escalation \(Elec\)](#) and [PT0027 Crossed Meters Escalation \(Gas\)](#).

Ref	When	Action	From	To	Interface	Means
12.10.1	Where the Initiating Supplier believes a Crossed Meter has occurred and within 2 WD s of establishing the identity of the Associated Supplier (s).	Send an Initial Request .	Initiating Supplier	Associated Supplier (s)	For Gas RMP(s) PT0055 Crossed Meter General Query (Gas) For Electricity RMP(s) Crossed Meters	SDES
12.10.2	Within 2 WD s of 12.10.1.	Acknowledge notification of the suspected Crossed Meter	Associated Supplier (s)	Initiating Supplier	For Gas RMP(s) PT0055 Crossed Meter General Query (Gas) For Electricity RMP(s) Crossed Meters	SDES
12.10.3	No later than the 5 th WD of receiving the Initial Request .	Return Initial Request with confirmation of: a) <i>Acceptance</i> – proceed to 12.10.5 or b) <i>Rejection</i> – proceed to 12.10.4.	Associated Supplier (s)	Initiating Supplier	For Gas RMP(s) PT0055 Crossed Meter General Query (Gas) For Electricity RMP(s) Crossed Meters	SDES
12.10.4	Following 12.10.3, if the Associated	Consider the rejection and determine the appropriate	Initiating Supplier	Associated Supplier (s)	For Gas RMP(s) PT0027 Crossed	Telephone or SDEP



	Supplier(s) rejects the Initial Request .	resolution steps: a) if the Initiating Supplier agrees there is no Crossed Meter, cease the procedure and take other corrective action; or b) contact the Associated supplier and if no agreement can be reached that a Crossed Meter has occurred, follow the procedure for escalations in Paragraph 3; or c) c) contact the Associated Supplier and if an agreement can be reached that a Crossed Meter has occurred, proceed to 12.10.5.			Meters Escalation (Gas) For Electricity RMP(s) PT0066 Crossed Meters Escalation (Elec)	
12.10.5	Following 12.10.3 or 12.10.4; if the Initiating Supplier and Associated Supplier agree that a site visit is required to resolve the Crossed Meter problem.	Request site visit to confirm address and meter details.	Initiating Supplier and / or Associated Suppliers(s)	Metering Equipment Manager(s)	For Gas RMP(s) Request Metering Job For Electricity RMP(s) Instruction on Action (D0005)	Email, IX, DTN DTN
12.10.6	Following 12.10.5 and within the	Carry out site visit and report findings to the relevant Energy	Metering Equipment	Initiating Supplier	As set out in the Metering Operations Schedule	



	timescales agreed with the Consumer .	Supplier .	Manager (s)	and/ or Associated Supplier (s)		
12.10.7	No later than 5 WD of receiving the results of the site visit or otherwise completing their investigation.	Share the results of site visit.	Initiating Supplier and / or Associated Supplier (s)	Initiating Supplier and / or Associated Supplier (s)	Agreed bilaterally	SDES
12.10.8	As soon as possible, following 12.10.7.	Agree changes to RMP data.	Initiating Supplier	Associated Supplier (s)		Not defined
12.10.9	As soon as reasonably practicable following agreement of the required changes to the RMP data.	Request that the data associated with the address or meter is updated. Note – where multiple RMP are impacted, all affected Energy Supplier s do not need to complete their investigations for data to be corrected.	Initiating Supplier and / or Associated Supplier (s) (in the case of Gas Supplier s, the update will be provided via the Shipper)	Metering Equipment Manager (s) CDSP ; SMRA , ERDA .	Using standard industry processes as set out in the Metering Operations Schedule or the Address Management Schedule	
12.10.10	As soon as reasonably practicable after receiving confirmation that the data has been updated.	The Registered Supplier for each RMP to provide confirmation that the problem has been resolved, including any other information that may be required by Paragraph 2.	Initiating Supplier and / or Associated Supplier (s) where	Consumer		Not defined



			applicable			
--	--	--	------------	--	--	--



Section E: Duplicate RMPs

13 Description of the Problem

- 13.1. A Duplicate RMP refers to an erroneous RMP that relates to the same gas or electricity supply as another valid RMP, resulting in the same consumption being billed against more than one RMP.
- 13.2. An Energy Supplier may first become aware of a potential Duplicate RMP when contacted by a Consumer, explaining that two or more Energy Suppliers are trying to charge them for the same fuel in the same period. The Consumer may or may not believe they have a relationship with one or more of the Energy Suppliers who are seeking to charge them.
- 13.3. Where a Switch occurs during a Duplicate RMP investigation, the Losing Supplier shall inform the Gaining Supplier of the ongoing investigation and give all reasonable assistance to the Gaining Supplier to ensure minimal disruption to the resolution.
- 13.4. Where a change of Supplier Agent(s) occurs during a Duplicate RMP investigation, the Energy Supplier shall ensure that both its outgoing and incoming Supplier Agents progress the resolution of the Duplicate RMP with minimum disruption to the resolution.
- 13.5. Where the Energy Supplier becomes aware that a new Consumer has moved into the premises before an identified metering issue has been resolved, the Energy Supplier shall ensure that the new Consumer is informed, and updated as to the progress, of the relevant resolution process.

14 Resolution Outcomes

- 14.1. In addition to the relevant requirements in Paragraph 2, the resolution of Duplicate RMPs needs to deliver the following minimum outcomes to be considered complete:
 - (a) the Duplicate RMP has been terminated within the Central Switching Service in accordance with the Switching Data Management Schedule;
 - (b) the Registration of the relevant Energy Supplier for the Duplicate RMP has been deactivated in accordance with the Registration Services Schedule; and
 - (c) the Energy Supplier with which the Consumer does wish to remain has been registered to the valid RMP in accordance with the Registration Services Schedule, where this is not already the case.

15 Resolution Process

- 15.1. When an [Energy Supplier](#) suspects or is notified of a potential [Duplicate RMP](#), it shall take all reasonable steps to investigate the issue in a timely manner with minimal negative impact to the [Consumer](#).
- 15.2. As part of its investigation, the [Energy Supplier](#) shall carry out the following checks:
- (a) confirm the [Consumer](#)'s preferred [Energy Supplier](#);
 - (b) identify the [Consumer](#)'s [Energy Contracts](#), and whether they contain fees linked to early termination;
 - (c) assess any meter exchange information;
 - (d) determine the location of the meter;
 - (e) confirm the asset details;
 - (f) identify the associated [Metering Equipment Manager](#) and [Meter Asset Provider](#);
 - (g) determine the current [Actual Meter Reading](#);
 - (h) confirm whether a new service has been installed or any changes have been made to the service at the premises; and
 - (i) confirm the address and whether there are any ambiguous mailing addresses.
- 15.3. The [Energy Supplier](#) may also:
- (a) confirm the address and asset details held by the [Metering Equipment Manager](#) (s) for both [RMPs](#);
 - (b) confirm whether the [Meter Serial Number](#) relates to any other premises within the [Enquiry Services](#); and
 - (c) carry out a site visit to confirm any uncertain details.
- 15.4. If, after investigation, the [Energy Supplier](#) determines that the [RMPs](#) relate to separate energy supplies and the issue is based on erroneous data held within the [Gas Central Data Service](#), [Supplier Meter Registration Service](#) and / or [Electricity Registration Data Service](#), then the [Energy Supplier](#) shall ensure the data is updated. This may require an update to the MPL Address to be progressed in accordance with the [Address Management Schedule](#).
- 15.5. If, after investigation, the [Energy Supplier](#) determines that a [Duplicate RMP](#) exists,

then it shall initiate the resolution process for [Duplicate RMPs](#) by raising an [Initial Request](#) in accordance with the interface table set out below.

- 15.6. The [Associated Supplier](#)(s) shall assist where possible in the investigation, providing all available information on the MPL Address, [Metering Asset](#) and [Consumer](#). The [Associated Supplier](#) shall make it clear to the [Initiating Supplier](#) if it is charging the [Consumer](#) and if these bills are being paid by the [Consumer](#).
- 15.7. All relevant historical meter readings shall be exchanged between the [Initiating Supplier](#) and [Associated Supplier](#)(s) with the aim of providing the [Consumer](#) with the best and most accurate bill or reconciliation of bills that may have already been paid by the [Consumer](#).
- 15.8. The [Initiating Supplier](#) and each [Associated Supplier](#) shall provide each other with any other information that may aid resolution of the problem.
- 15.9. For gas [RMPs](#), the following categorisation of [Duplicate RMPs](#) is used to facilitate resolution:
 - (a) [Supply Meter Points](#) with a status of 'dead' (as envisaged under processes within the [UNC](#));
 - (b) new services;
 - (c) liquid petroleum gas ([LPG](#)) development;
 - (d) address errors (specifically plot to postal addresses);
 - (e) [Consumer](#)-owned secondary meters; and
 - (f) unrecognised errors.
- 15.10. Where a gas [Duplicate RMP](#) is identified and categorised in accordance with Paragraph 15.9, the following additional information may help to determine which [RMP](#) is the valid [RMP](#) and which is the [Duplicate RMP](#):
 - (a) [Supply Meter Points](#) with a status of 'dead' - confirm the status of each [RMP](#) on the [Gas Enquiry Service](#); a status of dead may indicate historical activities by the [Gas Transporter](#) involving removal of supply;
 - (b) new services (including demolished / rebuilt or refurbished properties) - contact the [Consumer](#) to establish property history and carry out the following checks:
 - (i) confirm with the previous [Energy Supplier](#) (address, asset, meter readings, [Consumer](#) name, [Meter Point Reference Number](#));

- (ii) confirm with the gas [CDSP](#) how the [RMP](#) was loaded onto the [Gas Enquiry Service](#);
 - (iii) check council tax websites (http://www.voa.gov.uk/council_tax/) (<http://www.saa.gov.uk/>) (<http://ratinglists.vao.gov.uk/>) for evidence of ended or suspended payments; and
 - (iv) check if the new service is on an [IGT](#) network;
- (c) [IGT](#) network - confirm directly with the [IGT](#) using available websites and [Energy Supplier](#) contacts;
- (d) [LPG](#) development - confirm if the site resides within an [LPG](#) area. These developments can be confirmed by the gas [CDSP](#). Also contact the [Consumer](#) to confirm the gas supplies to neighbouring premises and check billing details;
- (e) address errors - confirm with the gas [CDSP](#) if any address amendments have been carried out and check the postal address file to see what address is held and if this matches any of the [RMPs](#) in question. Also contact the [Consumer](#) to confirm any known mailing addresses for the site; and
- (f) [Consumer](#)-owned secondary meters – contact the [Consumer](#) or carry out a site visit to confirm the following:
- (i) Is the meter a crimson colour?
 - (ii) Is there a regulator / governor in place?
 - (iii) Is the year of manufacture later than 2002?
 - (iv) Does the [Meter Serial Number](#) follow recognised configuration rules (confirm with manufacturer if unsure)?

15.11. For gas [RMPs](#), following investigation, the relevant [Gas Transporter](#) shall determine which [RMP](#) is valid and which is the [Duplicate RMP](#). In doing so, the [Gas Transporter](#) may take account of the factors described in Paragraph 15.10.



15.11A [Energy Supplier](#)s may use the [SDEP](#) to raise queries and otherwise securely exchange information related to Disputed Reads, using as appropriate [Market Message PT0056 - Duplicate Meter Points General Query \(Gas\)](#) and [PT0067 - Duplicate Meter Points General Query \(Elec\)](#).

15.12. The interface table below sets out the process and maximum timelines for resolving [Duplicate RMPs](#). If any steps are not completed in the timeline described, or are not completed satisfactorily, then the [Energy Supplier](#)s may initiate the escalation process described in Paragraph 3 using [Market Message PT0028 - Duplicate Meter Points Escalation \(Gas\)](#) and [PT0068 - Duplicate Meter Points \(Elec\) Escalation \(Elec\)](#).

Ref	When	Action	From	To	Interface	Means
15.12.1	Where the Initiating Supplier believes a Duplicate RMP has been created.	Establish the identity of the Associated Supplier(s) and send an Initial Request(s) .	Initiating Supplier	Associated Supplier(s)	For Gas RMP(s) PT0056 - Duplicate Meter Points General Query (Gas) For Electricity RMP(s) PT0067 - Duplicate Meter Points General Query (Elec)	SDEP
15.12.2	No later than 10 WDs after receiving the Initial Request .	Return the Initial Request with confirmation of: a) <i>Acceptance</i> – proceed to 15.12.4 or 15.12.9 for electricity or gas RMPs respectively; or b) <i>Rejection</i> – proceed to 15.12.3.	Associated Supplier(s)	Initiating Supplier	For Gas RMP(s) PT0056 - Duplicate Meter Points General Query (Gas) For Electricity RMP(s) PT0067 - Duplicate Meter Points General Query (Elec)	SDEP
15.12.3	Following 15.12.2, if the Associated	Consider the rejection and determine the appropriate	Initiating Supplier	Associated Supplier(s)	For Gas RMP(s) PT0028 - Duplicate Meter Points	Telephone or SDEP

	Supplier(s) rejects the Initial Request .	resolution steps: a) if the Initiating Supplier agrees there is no Duplicate RMP , cease the procedure and take other corrective action; or b) contact the Associated Supplier , and if no agreement can be reached that a Duplicate RMP has occurred, follow the procedure for escalations in Paragraph 3; or c) contact the Associated Supplier , and if an agreement can be reached that a Duplicate RMP has occurred, proceed to 15.12.4 or 15.12.9 for an electricity or gas RMP respectively.			Escalation (Gas) For Electricity RMP(s) PT0068 - Duplicate Meter Points Escalation (Elec)	
--	---	--	--	--	---	--

For Electricity [RMPs](#)

15.12.4	Following 15.12.2 or	Instruct MOA to logically	Duplicate	MOA	As set out in the Metering Operations	NA
---------	----------------------	---	-----------	---------------------	---	----

	15.12.3, if the Associated Supplier(s) accepts the Initial Request .	remove the meter and de-energise.	Supplier(s)		Schedule	
15.12.5	Following 15.12.4.	Submit request for logical disconnection of Duplicate RMP(s) .	Duplicate Supplier(s)	DNO	Details of Disconnection of Supply (D0132)	DTN
15.12.6	Following 15.12.5.	Confirm whether a Duplicate RMP exists and which RMPs are the Valid / Duplicate RMPs .	DNO	Duplicate Supplier(s)	Details of Disconnection of Supply (D0132)	DTN
15.12.7	Following 15.12.6, if the DNO determines that there is a Duplicate RMP .	Terminate the Duplicate RMP within CSS .	ERDS	CSS Duplicate Supplier(s)	As set out in the Switching Data Management Schedule	
15.12.8	Following 15.12.6 if the DNO determines that there is a Duplicate RMP .	Undertake relevant activities including deactivation of Registration in relation to the Duplicate RMPs , to ensure the relevant Electricity Supplier is registered at the Valid RMP .	Relevant Supplier	CSS	As set out in the Registration Services Schedule	

For Gas [RMPs](#)

15.12.9	Following 15.12.2 or 15.12.3, if the	Request that the relevant Shipper raises a Duplicate	Duplicate Supplier(s)	Relevant Shipper(s)		Not defined
---------	--------------------------------------	--	-----------------------	-------------------------------------	--	-------------

	Associated Supplier(s) accepts the Initial Request .	RMP with the gas CDSP .				
15.12.10	Following 15.12.9.	Assess whether a Duplicate RMP exists. Gas Supplier s and Shippers may make a recommendation on which RMP s are the Valid / Duplicate RMP s. Where required, the Shipper will seek resolution of the Duplicate RMP in accordance with the UNC .	Relevant Shipper(s)	Relevant Supplier(s)		Not defined
15.12.11	Following 15.12.10, if the gas CDSP determines that there is a Duplicate RMP(s)	Determine the Valid / Duplicate RMP and terminate the Duplicate RMP within CSS .	GRDS	CSS	As set out in the Switching Data Management Schedule	
15.12.12	Following 15.12.11	Undertake relevant activities including deactivation of Registration in relation to the Duplicate RMP s, to ensure the relevant Gas Supplier is registered at the Valid RMP .	Relevant Supplier	CSS	As set out in the Registration Services Schedule	



Section F: [Misdirected Payments](#)

16 Description of the Problem

- 16.1. This Section F describes requirements and processes for resolving [Misdirected Payments](#) in relation to [Prepayment Meters](#). The requirements described in this Section F do not apply to [Smart Meters](#) operating in prepayment mode.
- 16.2. A [Misdirected Payment](#) occurs when a [Consumer](#)'s payment is assigned to an [Energy Supplier](#) that does not have an [Energy Contract](#) for the relevant [RMP](#). As part of a [Switch](#), the [Gaining Supplier](#) shall provide a new [Prepayment Device](#) to the [Consumer](#) in accordance with the [Prepayment Arrangements Schedule](#). However, it is possible that the [Consumer](#) continues to use the [Prepayment Device](#) issued by the [Losing Supplier](#), a previous [Energy Supplier](#), or that they use a [Prepayment Device](#) issued for a different [RMP](#). [Misdirected Payments](#) may also occur due to incorrect data being held on [Systems](#).
- 16.3. Each [Energy Supplier](#) shall ensure that its contracted [Prepayment Meter Infrastructure Providers](#) ([PPMIPs](#)) meet the requirements of this Section F.
- 16.4. The [PPMIP](#) shall allocate [Consumer](#) payments received to the [Registered Supplier](#) to the [RMP](#) at the time of the credit purchase. For gas, the [PPMIP](#) shall allocate such payments using information held in its databases and for electricity, the [PPMIP](#) shall allocate payments using information held in the [Electricity Enquiry Service](#). Where the [PPMIP](#) cannot allocate such payments, these shall be unallocated. The process for managing [Unallocated Transactions](#) and contractual [PPMIP](#) obligations is set out in the [Prepayment Arrangements Schedule](#).

17 Resolution Outcomes

- 17.1. In addition to the relevant requirements in Paragraph 2, the resolution of [Misdirected Payments](#) must deliver the following minimum outcomes to be considered complete:
- (a) the [Consumer](#) has been issued with, or has confirmed that they have, the correct [Prepayment Device](#) for the [Energy Supplier](#) with the [Energy Contract](#);
 - (b) the [Gaining Supplier](#) has explained to the [Consumer](#) the implications of using the incorrect [Prepayment Device](#);
 - (c) [Misdirected Payments](#) having been reconciled between the [Initiating Supplier](#) and [Associated Supplier\(s\)](#); and
 - (d) where applicable, relevant records and systems have been updated with the correct data by the [Registered Supplier](#).

18 Resolution Process

- 18.1. It is the [Gaining Supplier](#)'s responsibility to manage the income received from its [Consumers](#) and as such it shall be able to identify when no payments or insufficient payments have been received from a [Consumer](#) with a [Prepayment Meter](#). When the [Gaining Supplier](#) believes that payments are missing, it shall contact the [Consumer](#) and initiate the resolution process for [Misdirected Payments](#).
- 18.2. A [Gaining Supplier](#) shall only make a claim in relation to a [Consumer](#) once. Therefore, the process should only be initiated once the [Gaining Supplier](#) is confident that the [Consumer](#) is correctly using the new [Prepayment Device](#).
- 18.3. Each [Energy Supplier](#) shall take reasonable steps to make a claim for any period of [Misdirected Payments](#) within two months of:
- (a) the [Consumer](#) commencing use of the correct [Prepayment Device](#);
 - (b) there being a change of [Metering Equipment](#) following which the old [Prepayment Device](#) is no longer used;
 - (c) the [Gaining Supplier](#) losing the [Consumer](#) via a subsequent [Switch](#) event;
 - (d) there being a [Change of Occupier](#);
 - (e) there being an [Erroneous Switch](#) agreed by the [Gaining Supplier](#) and [Losing Supplier](#), as described in Section B above; or
 - (f) there being a [Prepayment Device](#) issued in relation to a [Switch Request](#) that did not complete due to the [Registration Status](#) of the proposed [Registration](#) being [Cancelled](#).
- 18.4. Each [Energy Supplier](#) shall issue claims for [Misdirected Payments](#) on at least a monthly basis (or at the frequency agreed bilaterally between the [Initiating Supplier](#) and [Associated Supplier](#) for such claims).
- 18.5. If the [Initiating Supplier](#) requests there to be a change in the frequency of issuing claims, the [Initiating Supplier](#) shall provide the [Associated Supplier](#) with 20 [Working Days](#)' notice of the change.
- 18.6. A substantial increase is one where the number of claims in a period is expected to increase by more than 50% compared to the last period or if the total number of claims is to increase by more than 1,000 in any given month (or 250 in any given week if claims are made on a weekly basis). Where there is a substantial increase, the [Initiating Supplier](#) and [Gaining Supplier](#) shall enter a bilateral agreement for the handling of the excess. Under normal circumstances the [Associated Supplier](#) shall

not charge for passing [Misdirected Payments](#) to the [Initiating Supplier](#). However, where a subsequent claim is made for a [RMP](#) where there has already been a successful claim covering part of the same registration period, it is permitted for the [Associated Supplier](#) to charge a reasonable fee for passing-on any further [Misdirected Payments](#).

18.7. The [Gaining Supplier](#) shall not initiate the [Misdirected Payments](#) process:

- (a) if the [Misdirected Payments](#) cover less than 14 days' supply; or
- (b) if the [Misdirected Payments](#) relate to the period prior to the [Misdirected Payment](#) backstop. On 30 June each year, the [Misdirected Payments](#) backstop date will change to 30 June three years earlier for electricity and gas.

18.8. The [Initiating Supplier](#) shall ensure the claim only includes periods for which the [Associated Supplier](#) was registered to the [RMP](#). The [Associated Supplier](#) may reject any claims where the 'Claim Request From Date' or the 'Claim Request To Date' is not included.

18.9. Provided that the 'Claim Request From Date' of the claim period contained in the claim form is after the Supply End Date of the [Associated Supplier](#)'s registration, then the [Associated Supplier](#) shall process the claim form. The [Initiating Supplier](#) shall ensure that the claim form only includes claims for periods for which that Supplier was the [Registered Supplier](#) for the [Metering Points](#) concerned.

18.10. If there is no payment to be returned or only part payment, the 'Previous Supplier ID' field shall be completed where possible. This information will enable the [Initiating Supplier](#) to contact the previous [Energy Supplier](#), as the [Consumer](#) may be still using the [Prepayment Device](#) of that [Energy Supplier](#). The [Energy Supplier](#) receiving the money can then correctly allocate it to the appropriate [Consumer](#) accounts.

18.11. The [Losing Supplier](#) shall record and retain all payments received from a [Consumer](#) on or after the [Supply Effective From Date](#) of the [Gaining Supplier](#). The [Losing Supplier](#) shall not automatically refund any payments received after the [Supply Effective From Date](#) to the [Consumer](#) but shall instead allocate all such payments to the [Gaining Supplier](#) once requested to do so by the [Gaining Supplier](#) and refer all enquiries to the [Gaining Supplier](#).

18.12. In exceptional circumstances, if required, the [Gaining Supplier](#) can request an individual breakdown of payments, subsequent to the return of the claim form.



18.12A [Energy Suppliers](#) may use the [SDEP](#) to raise queries and otherwise securely exchange information related to [Misdirected Payments](#), using as appropriate [Market Message PT0053 - Misdirected Payments General Query \(Elec\)](#) and [PT0054 - Misdirected Payments General Query \(Gas\)](#).

18.13. The interface table below sets out the process and maximum timelines for resolving [Misdirected Payments](#). If any steps are not completed in the timeline described, or are not completed satisfactorily, then the [Energy Suppliers](#) may initiate the escalation process described in Paragraph 3 using [Market Message PT0023 - Misdirected Payments Escalation \(Elec\)](#) and [PT0038 - Misdirected Payments Escalation \(Gas\)](#).

Ref	When	Action	From	To	Interface	Means
18.13.1	Where the Initiating Supplier determines that a Misdirected Payment has occurred.	Send completed claim form for the Misdirected Payment(s) .	Initiating Supplier	Associated Supplier(s)	Claim Form provided on the REC Portal sent as: For Electricity RMP(s) PT0053 Misdirected Payments General Query (Elec) For Gas RMP(s) PT0054 Misdirected Payments General Query (Gas)	SDEP
18.13.2	Within 20 WDs of receiving the claim form.	Return the claim form with the reason codes, amount to be returned and any additional information included.	Associated Supplier(s)	Initiating Supplier	Claim Form provided on the REC Portal sent as: For Electricity RMP(s) PT0053 Misdirected Payments General Query (Elec) For Gas RMP(s)	SDEP

					PT0054 Misdirected Payments General Query (Gas)	
18.13.3	Within 10 WDs of 18.13.2.	Return the Misdirected Payment as specified in the returned claim form.	Associated Supplier(s)	Initiating Supplier	Not defined	Not defined

Section G: Debt Assignment

19 Description of the Problem

19.1. This Section G describes the requirements and process to be followed when assigning [Outstanding Charges](#) from the [Losing Supplier](#) to the [Gaining Supplier](#) in the event of a [Switch](#).

19.2. The scope of this section is limited to assignment of debt in relation to [Domestic Premises](#) and shall only be applicable where:

- (a) the [Consumer](#) has a debt and the repayment of which is scheduled on a [Prepayment Meter](#);
- (b) the [Consumer](#) has an [Energy Contract](#) with the [Gaining Supplier](#);
- (c) the [Gaining Supplier](#) has submitted a [Switch Request](#) in accordance with the [Registration Services Schedule](#);
- (d) the [Losing Supplier](#) has raised an [Objection](#) in accordance with the [Registration Services Schedule](#); and
- (e) the estimated value of the [Outstanding Charge](#) for assignment is between £20 and £500 (inclusive), including VAT.

19.3. The following are specifically excluded from the scope of this Section:

- (a) [RMPs](#) where a [Consumer](#)'s debt has been identified as [Complex Debt](#);
- (b) [RMPs](#) relating to [Non-Domestic Premises](#);
- (c) debt in relation to a [Consumer](#)'s account to which the applicable rate of VAT indicates that the [Consumer](#) is a [Non-Domestic Consumer](#);
- (d) [RMPs](#) where the debt is not being recovered via a [Prepayment Meter](#); and
- (e) assignment of estimated debt values below £20 or above £500 (inclusive of VAT).

19.4. The assignment of [Outstanding Charges](#) to the [Gaining Supplier](#) will include [Green Deal Charges](#) where relevant.

19.5. Nothing in this Section G shall preclude [Energy Suppliers](#) agreeing bilaterally to an assignment of:

- (a) [Complex Debt](#); or
- (b) debt outside the thresholds defined in Paragraph 19.2(e).

19.6. Where [Energy Suppliers](#) agree bilaterally to assign debt as described in Paragraph 19.5, they shall use the process set out under this Section G.

20 Resolution Outcomes

20.1. In addition to the relevant requirements in Paragraph 2, the [Gaining Supplier](#) and [Losing Supplier](#) shall ensure that:

- (a) the provisions of the relevant [Data Protection Legislation](#) are satisfied;
- (b) the VAT requirements in respect of bad debt relief are satisfied; and
- (c) all reasonable steps are taken to ensure that the [Consumer](#) does not experience any undue interruption or disruption to their expected repayment schedule.

21 Resolution Process

21.1. The debt assignment is initiated when a [Gaining Supplier](#) issues a Request for Debt Information [Market Message](#). The [Losing Supplier](#) will issue the Debt Information [Market Message](#) in response, indicating where applicable if the debt is [Complex Debt](#). Where the [Losing Supplier](#) identifies that the debt is [Complex Debt](#), the [Losing Supplier](#) shall keep a record of the reasons why a debt assignment request has been refused on the grounds of [Complex Debt](#) to support any follow up action on behalf of

the [Consumer](#).

- 21.2. The [Gaining Supplier](#) should issue a separate Request for Debt Information [Market Message](#) in relation to each impacted [RMP](#), even in the case of electricity [Related Metering Points](#).
- 21.3. Where a debt assignment is agreed, the [Gaining Supplier](#) will issue a Confirmation of Customer Debt Transfer [Market Message](#). Where the [Gaining Supplier's Registration](#) becomes [Active](#), then details of the [Total Debt Outstanding](#) are transferred to the [Gaining Supplier](#).
- 21.4. Where a [Losing Supplier](#) does not pay the [Factored Total Payment](#) in accordance with this Section G, the [Losing Supplier](#) may charge interest at LIBOR (for one-month GBP) plus two percentage points (without prejudice to other rights and remedies under this [Code](#)).
- 21.5. If at any point during the process, the [Switch Request](#) is cancelled, the debt assignment process will cease and the [Gaining Supplier](#) will inform the [Losing Supplier](#).
- 21.5A [Energy Suppliers](#) may use the [SDEP](#) to raise queries and otherwise securely exchange information related to [Misdirected Payments](#), using as appropriate [Market Message PT0051 Debt Assignment Protocol General Query \(Elec\)](#) and [PT0052 Debt Assignment Protocol General Query \(Gas\)](#).
- 21.6. The interface table below sets out the process and maximum timelines for initiating the debt assignment process. If any steps described in this Section G are not completed in the timeline described, or are not completed satisfactorily, then the [Energy Suppliers](#) may initiate the escalation process described in Paragraph 3 using [Market Message PT0022 Debt Assignment Protocol Escalation \(Elec\)](#) and [PT0037 Debt Assignment Protocol Escalation \(Gas\)](#). The interface table below sets out the process and maximum timelines for initiating the debt assignment process.



Ref	When	Action	From	To	Interface	Means
21.6.1	At the Point of Acquisition and as soon as reasonably practicable.	Provide DAP Privacy Notice to the Consumer , and inform the Consumer : a) that initiating the DAP is not a guarantee that debt assignment will be agreed; and b) that debt assignment requires the exchange of account information, including debt information, between the Energy Suppliers concerned.	Gaining Supplier	Consumer	Not defined	Not defined
21.6.2	Where the Losing Supplier has raised an Objection in accordance with the Registration Services Schedule and as soon as reasonably practicable.	Provide a DAP Privacy Notice to the Consumer where this has not previously been provided, and inform the Consumer : a) of the reason(s) for such Objection ; b) that the Consumer may apply for the assignment of Outstanding Charges to the Gaining Supplier to prevent future Objections ; and c) that the DAP will progress if this has been agreed with the Gaining Supplier .	Losing Supplier	Consumer	Not defined	Not defined
21.6.3	Within 4 WDs of receipt of the notice of Objection from the CSS Provider .	Issue a request for debt information.	Gaining Supplier	Losing Supplier	For Gas RMP(s) Request for Debt Information (G0806) For Electricity	DTN



					RMP(s) Request for Debt Information (D0306)	
21.6.4	Within 4 WDs of 21.7.3 or 21.7.6.	Validate the Market Message and proceed as follows: a) Acceptance (as set out in 21.7.1); or b) b) Rejection (as set out in 21.7.5).	Losing Supplier		Internal process	
21.6.5	Within 4 WDs of receipt of the request for debt information under 21.7.3 (or 21.7.6) and where the request is rejected.	Provide rejection flow.	Losing Supplier	Gaining Supplier	For Gas RMP(s) Request for Debt Information (G0806) For Electricity RMP(s) Request for Debt Information (D0306)	DTN
21.6.6	Within 3 WDs of receipt of the rejection as described in 21.7.5.	Send corrected request for debt information and proceed to step 21.7.4.	Gaining Supplier	Losing Supplier	For Gas RMP(s) Request for Debt Information (G0806) For Electricity RMP(s) Request for Debt	DTN

					Information (D0306)	
--	--	--	--	--	-------------------------------------	--

21.7. The interface table below sets out the process and maximum timelines for the provision of debt information.

Ref	When	Action	From	To	Information Required	Method
21.7.1	Within 4 WDs of receipt of the request for debt information under 21.7.3 (or paragraph 21.7.6) and where the request was not rejected under paragraph 21.7.4.	Send debt information, including estimate of likely Total Debt Outstanding .	Losing Supplier	Gaining Supplier	For Gas RMP(s) Return of Debt Information (G0807) For Electricity RMP(s) Return of Debt Information (D0307)	DTN
21.7.2	Following 21.8.1 or 21.8.4.	Validate the Market Message and proceed as follows: a) Acceptance (as set out in 21.9.1); or b) Rejection (as set out in 21.8.3).	Gaining Supplier		Internal process	N/A
21.7.3	Within 3 WDs of receipt of debt information as described in 21.8.1 or 21.8.4.	Provide rejection flow.	Gaining Supplier	Losing Supplier	For Gas RMP(s) Return of Debt Information (G0807) For Electricity RMP(s) Return of Debt Information (D0307)	DTN
21.7.4	Within 3 WDs after	Send corrected debt	Losing	Gaining	For Gas RMP(s)	DTN

	receipt of any debt information rejection as described in 21.8.3.	information.	Supplier	Supplier	Return of Debt Information (G0807) For Electricity RMP(s) Return of Debt Information (D0307)	
--	---	--------------	--------------------------	--------------------------	---	--

21.8. The interface table below sets out the process and maximum timelines for confirmation of debt assignment progression.

Ref	When	Action	From	To	Information Required	Method
21.8.1	Following 21.8.1 or 21.8.4 and where the request was not rejected under paragraph 21.8.3.	Review the information regarding the Outstanding Charges provided by the Losing Supplier and determine whether to progress with debt assignment under this Section.	Gaining Supplier		Internal process	N/A
21.8.2	As soon as reasonably practicable following paragraph 21.9.1, where the Gaining Supplier declines to undertake debt assignment.	Inform the Consumer that the Switch will not take place. The Gaining Supplier is not required to send a response to the debt information data flow (G0807 and/or D0307) to the Losing Supplier if it decides not to progress with the Switch. Where the response is not received by the Losing Supplier within 5 Working Days after	Gaining Supplier	Consumer	Reason for not progressing the Switch	Not defined



		21.8.1 applying, the debt assignment process will end.				
21.8.3	Within 5 WDs of 21.9.1, where the Gaining Supplier decides to progress with the debt assignment.	Provide confirmation of the debt to be transferred.	Gaining Supplier	Losing Supplier	For Gas RMP(s) Confirmation of Customer Debt Transfer (G0808) For Electricity RMP(s) Confirmation of Customer Debt Transfer	DTN
21.8.4	Following 21.9.3 or 21.9.6.	Validate the Market Message and proceed as follows: a) Acceptance (as set out in 21.10.1); or b) Rejection (as set out in 21.9.5).	Losing Supplier		Internal process	N/A
21.8.5	Within 3 WDs of receipt of debt confirmation as described in 21.9.3 or 21.9.6.	Provide rejection flow.	Losing Supplier	Gaining Supplier	For Gas RMP(s) Confirmation of Customer Debt Transfer (G0808) For Electricity RMP(s) Confirmation of Customer Debt Transfer (D0308)	DTN
21.8.6	Within 5 WDs of receipt of any debt confirmation rejection as described in 21.9.5.	Send corrected debt confirmation.	Gaining Supplier	Losing Supplier	For Gas RMP(s) Confirmation of Customer Debt Transfer (G0808) For Electricity RMP(s) Confirmation of Customer Debt	DTN

					Transfer (D0308)	
--	--	--	--	--	----------------------------------	--

21.9. The interface table below sets out the process and maximum timelines for re-submission of [Switch Request](#).

Ref	When	Action	From	To	Information Required	Method
21.9.1	Following 21.9.3 or 21.9.6, and where the request was not rejected under paragraph 21.9.5.	Provide Earliest Switch Request Re-submission Date .	Gaining Supplier	Losing Supplier	For Gas RMP(s) Confirmation of Customer Debt Transfer (G0808) For Electricity RMP(s) Confirmation of Customer Debt Transfer (D0308)	DTN
21.9.2	On, or no later than 2 WDs after, the Earliest Switching Request Re-Submission Date specified in accordance with 21.10.1.	Submit new Switch Request in accordance with Registration Services Schedule .	Gaining Supplier	CSS Provider	As set out on the Registration Services Schedule .	
21.9.3	If Switch Request has completed Validation and the CSS Message 'Invitation to Intervene' has been received by the Losing Supplier .	Do not raise an Objection in respect of the Switch Request .	Losing Supplier		Internal process	Not defined
21.9.4	If Switch Request is Rejected by the CSS .	Take reasonable steps to resolve the rejection and re-submit the Switch Request by no later than 2 Working Days after the Earliest	Gaining Supplier	CSS Provider	As set out on the Registration Services Schedule .	

		Switch Request Re-submission Date . The Losing Supplier and Gaining Supplier may agree to extend the re-submission timescale bilaterally.				
21.9.5	Directly following a Switch Request rejection that cannot be resolved as described in 21.10.4.	Issue notification that Switch cannot be completed.	Gaining Supplier	Losing Supplier ; and Consumer	Reason for not progressing Switch	Not defined

21.10. The interface table below sets out the process and maximum timelines for transfer of debt.

Ref	When	Action	From	To	Information Required	Method
21.10.1	Within 3 WDs of issuing the final bill to the Consumer notifying them of the Total Debt Outstanding .	Send notification of Total Debt Outstanding .	Losing Supplier	Gaining Supplier	For Gas RMP(s) Final Debt Details (G0809) For Electricity RMP(s) Final Debt Details (D0309)	DTN
21.10.2	Within 3 WDs of receipt of the confirmation of debt assigned data flow, as described 21.11.1 or 21.11.4.	Validate the Market Message and proceed as follows: a) Acceptance in 21.11.5; or b) Rejection in 21.11.3.	Gaining Supplier		Internal process	N/A
21.10.3	Within 3 WDs of receipt of the confirmation of debt assigned as	Provide rejection flow.	Gaining Supplier	Losing Supplier	For Gas RMP(s) Final Debt Details	DTN



	described in 21.11.2 or 21.11.4.				(G0809) For Electricity RMP(s) Final Debt Details (D0309)	
21.10.4	Within 3 WDs of receipt of any confirmation of debt assigned rejection as described in 21.11.3.	Send corrected confirmation of debt assigned data flow.	Losing Supplier	Gaining Supplier	For Gas RMP(s) Final Debt Details (G0809) For Electricity RMP(s) Final Debt Details (D0309)	DTN
21.10.5	Within 3 WDs of receipt of the confirmation of debt assigned data flow, as described in 21.11.2 or 21.11.4, and where it has not been rejected as described in 21.11.3.	Issue acceptance of the confirmation of debt assigned, which has the effect of transferring the debt from the Losing Supplier to the Gaining Supplier .	Gaining Supplier	Losing Supplier	For Gas RMP(s) Final Debt Details (G0809) For Electricity RMP(s) Final Debt Details (D0309)	DTN

21.11. The interface table below sets out the process and maximum timelines for payment of the [Factored Total Payment](#).

Ref	When	Action	From	To	Information Required	Method
21.11.1	Following acceptance of confirmation of debt assigned data flow as described in 21.11.5.	Calculate Factored Total Payment based on the Total Debt Outstanding .	Losing Supplier		Internal process	N/A
21.11.2	On or after the 12th WD of	Issue consolidated invoice	Losing	Gaining	Consolidated invoice	Secure



	each month, but no earlier than a period of at least 10 WDs has elapsed since the issue of any given assigned debt data flow as described in 21.11.5.	for all RMPs for which the Losing Supplier received a confirmation of debt assigned data flow during the previous month.	Supplier	Supplier	and supporting electronic spreadsheet or CSV file in the format set out in the annex to this Section G.	encrypted means
21.11.3	Within 5 WDs following receipt of consolidated invoice as described in 21.12.2.	Validate consolidated invoice and raise a query / dispute in accordance with Paragraph 3.	Gaining Supplier	Losing Supplier	For Gas RMP(s) PT0037 Debt Assignment Protocol Escalation (Gas) For Electricity RMP(s) PT0022 Debt Assignment Protocol Escalation (Elec)	SDEP
21.11.4	Within 28 days of 21.12.2	Make payment.	Gaining Supplier	Losing Supplier		Not defined



Section G, Annex - Format of [DAP](#) Spreadsheet to Support Invoicing

DAP Invoice Reference	Invoice Month/Year	Supplier Name (who is being invoiced)						
XXXXXX	XX/XXX X	XXXXXX						
	MPAN/MPRN	Customer Name	Total Debt Outstanding (£)	VAT element (£)	Total amount excluding VAT (£)	90% of excluded VAT element (£)	Factored Total Payment (90% of excluding VAT total plus VAT) (£)	Factored Total Payment entered manually (£)
Example:	1234567890	Mr John Smith	£ 20.00	£ 0.95	£ 19.05	£ 17.14	£ 18.10	
	Totals			£ 0.95	£ 19.05	£ 17.14	£ 18.10	

~~Appendix 1: Advanced Meter Half-Hourly Data Sharing template~~

~~The Advanced Meter Half-Hourly Data Sharing template can be accessed through the following link:~~

~~<https://recportal.co.uk/operational-documents>~~